


## 600 LUMEN LINEAR FLUORESCENT EM. BALLAST

Page 1 of 2

### FBP90



### Features

**Illumination:** The FBP90 provides 90 minutes of emergency illumination by utilizing existing fluorescent lighting and produces 500-600 lumens initial emergency light output. The FBP90 can be used with most 17-40 W (2'-4') T8, T10, or T12 fluorescent lamps without integral starters, including U-shaped, energy saving, and 4-pin compacts. It is also compatible with most 1-, 2-, 3-, and 4-lamp electronic, standard, energy saving and dimming AC ballasts. See lamp operation for specific lamp types.

**Housing:** Housing is constructed of 20 gauge steel with a high temperature powder coat paint finish. Slim housing allows for wireway channel mounting on most lighting fixtures.

**Operating Temperature Range:**  
32°F (0°C) to 131°F (55°C)

### Electronics: 120/277 VAC

dual voltage input with surge protected, solid-state charging circuitry provides for a reliable charging system. Charging system is complete with AC indicator lamp and test switch.

### Electrical Specifications:

Input Power: 4 W max.

### Battery

Maintenance free, sealed nickel cadmium battery. Supplies 90 minutes of emergency power. Estimated service life of 10 years.

**Lamp Operation<sup>1</sup>:** Operates the following lamp types<sup>2</sup>:

T8 linear fluorescent (two lamp operation)  
T12 linear fluorescent  
T9 circline  
T12 U-bent  
T5 long compact fluorescent

Notes:

1) Consult factory for compatibility, operation and performance of product with lamp types not listed.

2) See table 1 on back for specific lamp performance and operation.

### Code Compliance

UL 924 and optional UL damp location listed. NFPA 70, NFPA 101, NEC, BOCA, OSHA and IBC illumination standards. Suitable for use in sealed and gasketed luminaires.

### Warranty

One year full electronics warranty. One year full battery warranty.

### Job Information Type:

Job Name:

Cat. No.:

Notes:

## 600 LUMEN LINEAR FLUORESCENT EM. BALLAST

Page 2 of 2

### Ordering Information

**FBP90**

Series

Options

**FBP90** = 600 Lumen Max. Output  
Fluorescent Emergency Ballast for One  
Lamp Operation

**EX**<sup>1</sup> = Special Input Transformer  
(specify voltage and frequency)  
**DL** = Damp Location Listing

#### Accessories (order as a separate item)

**CCAPS** = Wire Cover Kit for External Mounting

**RTS** = Remote Test Plate

**RTS2** = Remote Test Switch & Pilot Light Kit (includes plate)

#### Note

1) Some option combinations may impact UL listing. Consult factory for specifics.

### Lamp Operation and Performance

Table 1

LAMP TYPE	WATT.	BASE TYPE	NON-EMERGENCY MAX. LUMEN OUTPUT	EMERGENCY OP. MAX. LUMEN OUTPUT	EMERGENCY LAMP OPERATION
F20T12	20	G13/Med Bi-Pin	1275	500-600	One
F30T12	30	G13/Med Bi-Pin	2350	500-600	One
F40T12	40	G13/Med Bi-Pin	2650	500-600	One
F40T12/U	40	G13/Med Bi-Pin	3100	500-600	One
F48T10	110	R17D/Recessed	6200	500-600	One
F17T8	17	G13/Med Bi-Pin	1350	500-600	One
F25T8	25	G13/Med Bi-Pin	2150	500-600	One
F32T8	32	G13/Med Bi-Pin	2950	500-600	One
F32T8/U	32	G13/Med Bi-Pin	2700	500-600	One
F40T8	40	G13/Med Bi-Pin	3725	500-600	One
FC6T9	20	G10Q/4-Pin	800	500-600	One
FC8T9	22	G10Q/4-Pin	1100	500-600	One
FC12T9	32	G10Q/4-Pin	1950	500-600	One
FC16T9	40	G10Q/4-Pin	2700	500-600	One
F39/36BX	39	2G11/4-Pin	2850	500-600	One
F40/30BX	40	2G11/4-Pin	3150	350-450	One

#### NOTES

- 1) Maximum non-emergency lumen output can vary based on lamp manufacturer, ambient operating temperature, and ballast manufacturer.
- 2) Maximum emergency lumen output is based on total output of one or two lamps, and can vary based on lamp manufacturer and ambient operating temperature.
- 3) Consult factory for compatibility, operation and performance of lamp types not listed.



Philips Lightolier  
e: [lol.webmaster@philips.com](mailto:lol.webmaster@philips.com)  
t: (508) 679-8131  
w: [www.lightolier.com](http://www.lightolier.com)

FBP90 August 28, 2012

Specifications are subject to change without notice.  
© Koninklijke Philips Electronics N.V., 2012. All rights reserved.

**Job Information** **Type:**